



MV Central Storage inverters S9900TL

935kW - 1.000V

Technical data

Type code	S9900TL
Battery voltage range (V_{dc}) ¹⁾	625 - 1.000 V
DC voltage range at the max. power (V_{dc})	645 - 1.000 V
Battery type	Li-on, Lead, Ni-Cd, NaNiCl ₂
Absolute maximum voltage (V_{dc})	1.000
Maximum input current (A_{dc}) @25° of ambient temperature	1.600 A
Voltage ripple (%)	<2%
Number of input max in parallel	4
Overvoltage Protection	SPD varistor device Class II (Opt. Class I-II)
DC input connection	DC Switch under load
Reverse polarity protection	Yes
AC Output grid	
Max Power (kW) ¹⁾	935 kW
Max Apparent Power (kVA)	935 kVA
Maximum Current (A_{ac})	1.460 A
Max unbalance current	< 2%
Nominal Voltage (V_{ac})	370 V_{RMS}
Nr. Phase	3-phase (L1 - L2 - L3 - PE)
Frequency (Hz)	50/60 Hz
Aux. supply (Normal line)	230 V_{ac} - 16A - 50/60Hz (L-N)
Auxiliary supply (Preferential line)	230 V_{ac} - 10A - 50/60Hz (L-N)
Distortion factor (THDi) ²⁾	<3%
Power Factor ³⁾	From 0 to 1 inductive or capacitive
Galvanic insulation	No (transformerless)
AC input connection	Magnetothermic circuit breaker (MCCB)
General Data	
Maximum efficiency	98.90%
European efficiency	98.6%
Night consumption (W)	< 60 W
Weight (kg)	1.600 kg
Protection degree	IP20
Cooling	Air forced cooling fan speed controlled
Air Flow	4.800 m ³ /h
Maximum power dissipated in overload condition	24,9 kW - 21.410 Kcal/h
Dimensions (W x D x H)	2.400x760x2.240 mm
Noise level (dBA)	< 70 dBA
Operating temperature (°C)	-10° C +50° C
Storage temperature (°C)	-20° C +60° C
Humidity (Not condensing) (%)	0 - 95%
Height above the sea (without derating) ⁴⁾	1.000 m
Overvoltage Category	II
Color	RAL 9006

1) Valid at P.F.= 1 and Vac nominal.

2) THDi is lower than 3% for inverter power greater than 25%.

3) P-Q capability is semicircular.

4) From 45°C to 53°C derating of power.

5) Above 1.000m a.s.l. derating of the power of 1% per 100 m. (contact factory for details).

Note: Each inverter must be connected separately to its own LV/MV transformer or it has to be connected to a separate LV secondary input of the LV/MV transformer. Two or more inverters cannot be connected in parallel to the same LV secondary input of the LV/MV transformer.

Remark. Features not specifically listed in the present data sheet are not included in the product



For more information please contact your local FIMER representative or visit:

fimer.com

We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. FIMER does not accept any responsibility whatsoever for potential errors or possible lack of information in this document.

We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilization of its contents – in whole or in parts – is forbidden without prior written consent of FIMER. Copyright© 2020 FIMER. All rights reserved.

